



GENERATING SET GE 11000 HBS/GS

- Honda OHV petrol engine
- Engine shut down for low oil level
- Single-Phase synchronous alternator
- Suitable for electronic equipments
- Sockets: 1x230V 32A 2P+T CEE - 1x230V 16A 2P+T CEE
1x230V 16A 2P+T SCHUKO
- ELCB-GFI (Ground Fault Interruptor)
- Circuit breaker
- Protective frame
- Meets EC directives



Standard Equipment										
	Petrol engine	Air cooling	Electric Starter	Battery 12V	Oil pressure Indicator	Engine shut down (oil)	Hours-meter			
	Synchronous alternator	Sockets	ELCB-GFI	Circuit breaker	Thermal shut off	Voltmeter				

- Options on request
- Earthing kit
 - Hand trolley CTM10

Technical data GE 11000 HBS/GS

A.C. GENERATION - 50 Hz - Single-Phase synchronous alternator, self-excited, self-regulated, brushless

* Stand-by single-phase power	11 kVA (9.9 kW) / 230 V / 47.8 A
* PRP single-phase power	10 kVA (9 kW) / 230 V / 43.5 A
Cos φ	0.9
Insulation class	H

* Output powers according to ISO 8528-1

ENGINE - 4-stroke petrol, OHV, Air cooling

Model	Honda GX 630
* Stand-By net power	14.5 kW (19.7 HP)
* PRP net power	10.5 kW (14.3 HP)
Cylinders/ Displacement	2/ 688 cm ³
Speed	3000 rpm
Fuel consumption (75% of PRP)	3.9 l/h

* Powers according to SAE J1349

GENERAL SPECIFICATIONS

Tank capacity	18 l
Running time (75% of PRP)	4.5 h
IP protection degree	IP 23
*Dimensions LxIxh (mm)	935x525x645
*Dry weight	145 kg
**Acoustic power LwA (pressure LpA)	99 dB(A)(74 dB(A) @ 7m)

* Dimensions and weight without trolley/trailer. / **For fixed installation only in the EU market

Maahantuoja: ENDE-HITSI OY

Aallonkohana 2 A 4 02320 Espoo
puh. 050-4729304, 09-2219370
www.endehitsi.fi
ende-hitsi@endehitsi.fi

Mosa reserves the right to change this specification without notice. For further information please contact the sales department.